IP Link® Device Interface
Ethernet Communication Sheet

This document provides additional assistance with wiring your Extron IP Link enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific Extron IP Link enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type:	Video Projector
Manufacturer:	Epson
Firmware Version:	N/A
Model(s):	BrightLink Pro 1410Wi, EB-1410WT

Minimum Software and Firmware Requirements:

IP Link Compiler	IP Link Firmware	GC Version
1.6.0	1.17	3.5.0

Version History:

Driver Version	Date	Notes
1	7/10/2013	Extron Certified version. Tested on BrightLink Pro 1410Wi

Driver Notes:

- Driver has been optimized for Volume.

Control Commands & States:

Aspect Ratio	16:9	Auto	Full
	Zoom	Native	
Auto Image	Execute		
AV Mute	On	Off	
Closed Caption	CC1	CC2	Off
Freeze	On	Off	
Input	Auto	RGB	Component
	HDMI	Video	USB Display
	USB 1	USB 2	LAN
	Whiteboard	Display Port	
Lamp Mode	Normal	Eco	
Menu Navigation	Up	Down	Left
	Right	Menu	Enter
Power Control	On	Off	
Volume (Discrete)	0 to 20 in steps of 1		
Volume (Step)	Up	Down	

Status Available:

Aspect Ratio	16:9	Auto	Full
	Zoom	Native	
AV Mute	On	Off	
Closed Caption	CC1	CC2	Off
Connection Status	Connected	Disconnected	
Freeze	On	Off	
Input	Auto	RGB	Component
	HDMI	Video	USB Display
	USB 1	USB 2	LAN
	Whiteboard	Display Port	
Lamp Mode	Normal	Eco	
Lamp Usage	Hours		
Power Control	On	Off	
Power Status	On	Off	Cooling Down
	Warming Up	Status Unavailable	
Volume (Discrete)	0 to 20 in steps of 1		

Network communication:

When configuring the Ethernet driver, be sure device settings match that of the GC configuration.

Port Type:	Ethernet
Logon Credentials Supported:	No
Default Port:	3629
Multi-Connection Capable:	No
Port Changeable:	Yes

Ethernet Driver Configuration Description:

Please refer to user manual for settings and changes to the network communication parameters such as Port Number.

Notes for the Device: